

Pioneer

PROFESSIONAL DJ MIXER

DJM-2000/2000nexus

Firmware Update Manual

Contents

| | |
|--|--------|
| DJM-2000/2000nexus Update Manual for Windows® 8 | - 3 - |
| DJM-2000/2000nexus Update Manual for Windows® 7 | - 9 - |
| DJM-2000/2000nexus Update Manual for Windows Vista®..... | - 15 - |
| DJM-2000/2000nexus Update Manual for Windows® XP | - 21 - |
| DJM-2000/2000nexus Update Manual for Mac OS®..... | - 25 - |
| Check the current version of DJM-2000/2000nexus | - 28 - |
| Error Message and Details (for Windows) | - 29 - |
| Error Message and Details (for Mac OS) | - 30 - |

DJM-2000/2000nexus Update Manual for Windows® 8

A . Check the unzipped file:

1. Unzip the downloaded file

Right click the downloaded file and select "Extract All" from the menu to unzip the file.

2. Check the unzipped file


When the zip file is unzipped, the "DJM-2000_vxxx" folder is generated.

Please ensure the following files are included in the folder.

1. DJM2000_vxxx.exe
2. DJM2000_vxxx.upd

- ✓ xxx is the version of the new firmware.
- ✓ Extension (.exe or .upd) might not be shown depending on your computer settings.

B . Setup DJ Mixer for updating:



< STEP1 >

While holding [ON/ OFF (BEAT EFFECT)] and [ON/ OFF (TOUCH PANEL EFFECT)] buttons, press the Power button to go into update mode.

< STEP2 >

Please check the current version of your firmware by checking the "Current version" on the touch panel.
 (If the current version, **x.xx**, is displayed, you do not need to continue the update process.
 The latest firmware has already been installed.)

< STEP3 >


Connect your computer to DJ Mixer using a LAN cable.

Connect the LAN cable to the port of [COMPUTER 1 or 2] on the rear panel of your DJ Mixer.


C . Update the firmware from your computer:

1. Change network settings


< STEP1 > Open "Control Panel" > "Network and Internet" > "Network Connections".




< STEP2 > Open "Network and Sharing Center".




< STEP3 > Open "Change adapter setting".




< **STEP4** > Open "Properties" of the network device where DJ Mixer is connected.
(Right click on the icon > "Properties")



< **STEP5** > Select "Internet Protocol Version 4(TCP/IPv4) and click "Properties".




< **STEP6** > Select "Obtain an IP address automatically" and "Obtain DNS server address automatically".




< **STEP7** > Press "OK" to close the Network Connections dialog box.


< **STEP8** > Right click the task bar and select "Properties".



< **STEP9** > Select "Notification area" > "Customize".



< **STEP10** > Select "Show icon and notifications" for network.



< **STEP11** > Close "Properties" by pressing the "OK" button.

2. Make sure that your DJ Mixer and computer are connected

Find an icon on the task bar (right-bottom of your screen) to identify the connection status.


| Icon | Message | Connection status |
|------|----------------------|---|
| | Not Connected | LAN cable is not connected. Make sure that the cable is properly connected. |
| | Identifying... | Identifying connection. Wait for the connection to be established. It may take about one minute. |
| | Unidentified network | DJ Mixer is connected. It is ready to start the update tool. |

3. Start updating your firmware

- ✓ Close all the applications before you start updating.
- ✓ Depending on the firewall setting of your security software and/or operating system, your computer and mixer may not be connected properly. In such a case, you need to exempt the update tool (DJM2000_vxxx.exe) from your firewall settings.
Please contact customer support of the security software provider and/or operating system for further details regarding firewall settings.

< **STEP1** > Double click "DJM2000_vxxx.exe".
Start update tool.

< **STEP2** > Select a language from the dropdown list and click "OK".




< **STEP3** > Start updating by pressing "START".

- ✓ DO NOT remove power cable and/ or LAN cable during the update.
- ✓ If the Connect dialog box keeps appearing for 30 seconds or longer, the network connection might not be established. Press the "EXIT" button and try connecting the network again to update.



- < **STEP4** > Make sure that the update process has been completed.
The following "update completed" message appears when the progress bar on the touch panel reaches 100%.



- < **STEP5** > Restart DJ Mixer.
- ✓ If any changes were made in the above "1. Change network settings" of this chapter, please restore the network settings to the previous values.

DJM-2000/2000nexus Update Manual for Windows® 7

A . Check the unzipped file:

1. Unzip the downloaded file

Right click the downloaded file and select "Extract All" from the menu to unzip the file.

2. Check the unzipped file


When the zip file is unzipped, the "DJM-2000_vxxx" folder is generated.

Please ensure the following files are included in the folder.

1. DJM2000_vxxx.exe
2. DJM2000_vxxx.upd

- ✓ xxx is the version of the new firmware.
- ✓ Extension (.exe or .upd) might not be shown depending on your computer settings.

B . Setup DJ Mixer for updating:



< STEP1 >

While holding [ON/ OFF (BEAT EFFECT)] and [ON/ OFF (TOUCH PANEL EFFECT)] buttons, press the Power button to go into update mode.

< STEP2 >

Please check the current version of your firmware by checking the "Current version" on the touch panel.
 (If the current version, **x.xx**, is displayed, you do not need to continue the update process.
 The latest firmware has already been installed.)

< STEP3 >


Connect your computer to DJ Mixer using a LAN cable.

Connect the LAN cable to the port of [COMPUTER 1 or 2] on the rear panel of your DJ Mixer.


C . Update the firmware from your computer:

1. Change network settings


< STEP1 > Open "Control Panel" > "Network and Internet" > "Network Connections".




< STEP2 > Open "Network and Sharing Center".




< STEP3 > Open "Change adapter setting".




< **STEP4** > Open "Properties" of the network device where DJ Mixer is connected.
(Right click on the icon > "Properties")



< **STEP5** > Select "Internet Protocol Version 4(TCP/IPv4) and click "Properties".




< **STEP6** > Select "Obtain an IP address automatically" and "Obtain DNS server address automatically".




< **STEP7** > Press "OK" to close the Network Connections dialog box.


< **STEP8** > Right click task bar and select "Properties".



< **STEP9** > Select "Notification area" > "Customize".






< **STEP10** > Select "Show icon and notifications" for network.



< **STEP11** > Close "Properties" by pressing the "OK" button.

2. Make sure that your DJ Mixer and computer are connected

Find an icon on the task bar (right-bottom of your screen) to identify the connection status.

| Icon | Connection Status |
|---|---|
|  | LAN cable is not connected. Make sure that the cable is properly connected. |
|  | Identifying connection. Wait for the connection to be established. It may take about one minute. |
|  | DJ Mixer is connected. It is ready to start the update tool. |


3. Start updating your firmware

- ✓ Close all the applications before you start updating.
- ✓ Depending on the firewall setting of your security software and/or operating system, your computer and mixer may not be connected properly. In such a case, you need to exempt the update tool (DJM2000_vxxx.exe) from your firewall settings.

Please contact customer support of the security software provider and/or operating system for further details regarding firewall settings.

< **STEP1** > Double click "DJM2000_vxxx.exe".
Start update tool.

< **STEP2** > Select a language from the dropdown list and click "OK".




< **STEP3** > Start updating by pressing "START".

- ✓ DO NOT remove power cable and/ or LAN cable during the update.
- ✓ If the Connect dialog box keeps appearing for 30 seconds or longer, the network connection might not be established. Press the "EXIT" button and try connecting the network again to update.



- < **STEP4** > Make sure that the update process has been completed.
The following "update completed" message appears when the progress bar on the touch panel reaches 100%.



- < **STEP5** > Restart DJ Mixer.
- ✓ If any changes were made in the above "1. Change network settings" of this chapter, please restore the network settings to the previous values.

DJM-2000/2000nexus Update Manual for Windows Vista®

A . Check the unzipped file:

1. Unzip the downloaded file

Right click the downloaded file and select "Extract All" from the menu to unzip the file.

2. Check the unzipped file


When the zip file is unzipped, the "DJM-2000_vxxx" folder is generated.

Please ensure the following files are included in the folder.

1. DJM2000_vxxx.exe
2. DJM2000_vxxx.upd

- ✓ xxx is the version of the new firmware.
- ✓ Extension (.exe or .upd) might not be shown depending on your computer settings.

B . Setup DJ Mixer for updating:



< STEP1 >


While holding [ON/ OFF (BEAT EFFECT)] and [ON/ OFF (TOUCH PANEL EFFECT)] buttons, press the Power button to go into update mode.

< STEP2 >

Please check the current version of your firmware by checking the "Current version" on the touch panel.
(If the current version, **x.xx**, is displayed, you do not need to continue the update process.
The latest firmware has already been installed.)

< STEP3 >

Connect your computer to DJ Mixer using a LAN cable.




Connect the LAN cable to the port of [COMPUTER 1 or 2] on the rear panel of your DJ Mixer.


C . Update the firmware from your computer:

1. Change network settings


< STEP1 > Open "Control Panel" > "Network and Internet" > "Network Connections".




< STEP2 > Open "Network and Sharing Center".




< STEP3 > Open "Change adapter setting".




< **STEP4** > Open "Properties" of the network device where DJ Mixer connected.
(Right click on the icon > "Properties")



< **STEP5** > Select "Internet Protocol Version 4(TCP/IPv4) and click "Properties".




< **STEP6** > Select "Obtain an IP address automatically" and "Obtain DNS server address automatically".




< **STEP7** > Press "OK" to close the Network Connections dialog box.

< **STEP8** > Right click the task bar and select "Properties".






< **STEP9** > Select "Notification area" and check "Network".



< **STEP10** > Close "Properties" by pressing the "OK" button.

2. Make sure that your DJ Mixer and computer are connected

Find an icon on the task bar (right-bottom of your screen) to identify the connection status.

| | | | |
|----------------------------------|--|---|---|
| <p>Message & Icon</p> | <p>Not Connected</p> <p>You are currently not connected to any networks.</p>  | <p>Currently connected to:</p> <p>Identifying... Access: Limited Connectivity</p>  | <p>Currently connected to:</p> <p>Unidentified network Access: Limited Connectivity</p>  |
| <p>Connection status</p> | <p>LAN cable is not connected. Make sure that the cable is properly connected.</p> | <p>Identifying connection. Wait for the connection to be established. It may take about one minute.</p> | <p>DJ Mixer is connected. It is ready to start the update tool.</p> |


3. Start updating your firmware

- ✓ Close all the applications before you start updating.
- ✓ Depending on the firewall setting of your security software and/or operating system, your computer and mixer may not be connected properly. In such a case, you need to exempt the update tool (DJM2000_vxxx.exe) from your firewall settings.

Please contact customer support of the security software provider and/or operating system for further details regarding firewall settings.

< **STEP1** > Double click "DJM2000_vxxx.exe".
Start update tool.

< **STEP2** > Select a language from the dropdown list and click "OK".




< **STEP3** > Start updating by pressing "START".

- ✓ DO NOT remove power cable and/ or LAN cable during the update.
- ✓ If the Connect dialog box keeps appearing for 30 seconds or longer, the network connection might not be established. Press the "EXIT" button and try connecting the network again to update.



- < **STEP4** > Make sure that the update process has been completed.
The following "update completed" message appears when the progress bar on the touch panel reaches 100%.



- < **STEP5** > Restart DJ Mixer.
- ✓ If any changes were made in the above "1. Change network settings" of this chapter, please restore the network settings to the previous values.

DJM-2000/2000nexus Update Manual for Windows® XP

A . Check the unzipped file:

1. Unzip the downloaded file

Right click the downloaded file and select "Extract All" from the menu to unzip the file.

2. Check the unzipped file


When the zip file is unzipped, the "DJM-2000_vxxx" folder is generated.

Please ensure the following files are included in the folder.

1. DJM2000_vxxx.exe
2. DJM2000_vxxx.upd

- ✓ xxx is the version of the new firmware.
- ✓ Extension (.exe or .upd) might not be shown depending on your computer settings.

B . Setup DJ Mixer for updating:



< STEP1 >


While holding [ON/ OFF (BEAT EFFECT)] and [ON/ OFF (TOUCH PANEL EFFECT)] buttons, press the Power button to go into update mode.

< STEP2 >

Please check the current version of your firmware by checking the "Current version" on the touch panel.
 (If the current version, **x.xx**, is displayed, you do not need to continue the update process.
 The latest firmware has already been installed.)

< STEP3 >

Connect your computer to DJ Mixer using a LAN cable.




Connect the LAN cable to the port of [COMPUTER 1 or 2] on the rear panel of your DJ Mixer.


C . Update the firmware from your computer:

1. Change network settings

< **STEP1** > Open "Start" > "Setting" > "Control Panel" > "Network Connections".




< **STEP2** > Open "Properties" of the network device where DJ Mixer is connected.
(Right click on the icon > "Properties")




< **STEP3** > Check the box of "Notify me when this connection has limited or no connectivity".

< **STEP4** > Select "Internet Protocol (TCP/IP) and click "Properties".



< **STEP5** > Select "Obtain an IP address automatically" and "Obtain DNS server address automatically".



< **STEP6** > Press "OK" to close the Network Connections dialog box.

2. Make sure that your DJ Mixer and computer are connected

Find an icon on the task bar (right-bottom of your screen) to identify the connection status.


| Icon | Connection status |
|------|---|
| | LAN cable is not connected. Make sure that the cable is properly connected. |
| | Identifying connection. Wait for the connection to be established. It may take about one minute. |
| | DJ Mixer is connected. It is ready to start the update tool. |

3. Start updating your firmware

- ✓ Close all the applications before you start updating.
- ✓ Depending on the firewall setting of your security software and/or operating system, your computer and mixer may not be connected properly. In such a case, you need to exempt the update tool (DJM2000_vxxx.exe) from your firewall settings.
Please contact customer support of the security software provider and/or operating system for further details regarding firewall settings.

< **STEP1** > Double click "DJM2000_vxxx.exe".
Start update tool.

< **STEP2** > Select a language from the dropdown list and click "OK".




< **STEP3** > Start updating by pressing "START".

- ✓ DO NOT remove power cable and/ or LAN cable during the update.
- ✓ If the Connect dialog box keeps appearing for 30 seconds or longer, the network connection might not be established. Press the "EXIT" button and try connecting the network again to update.



< **STEP4** > Make sure that the update process has been completed.

The following "update completed" message appears when the progress bar on the touch panel reaches 100%.



< **STEP5** > Restart DJ Mixer.

- ✓ If any changes were made in the above "1. Change network settings" of this chapter, please restore the network settings to the previous values.

DJM-2000/2000nexus Update Manual for Mac OS®

A . Check the unzipped file:

1. Unzip the downloaded file

Double click the downloaded file, and select "Extract ALL" from the menu to unzip the file.

2. Check the unzipped file


When the zip file is unzipped, the "DJM-2000_vxxx" folder is generated.

Please ensure the following files are included in the folder.

1. DJM2000_vxxx

✓ xxx is the version of the new firmware.

B . Setup DJ Mixer for updating:



< STEP1 >

While holding [ON/ OFF (BEAT EFFECT)] and [ON/ OFF (TOUCH PANEL EFFECT)] buttons, press the Power button to go into update mode.

< STEP2 >


Please check the current version of your firmware by checking the "Current version" on the touch panel.

(If the current version, x.xx, is displayed, you do not need to continue the update process.

The latest firmware has already been installed.)

< STEP3 >

Connect your computer to DJ Mixer using a LAN cable.



Connect the LAN cable to the port of [COMPUTER 1 or 2] on the rear panel of your DJ Mixer.

C . Update the firmware from your computer:

1. Change network settings

Open "System Performance" > "Network" > "Ethernet" > "Using DHCP".

2. Make sure that your DJ Mixer and computer are connected

Identify the connection status in "System Performance" > "Network" > "Ethernet".


| | | |
|--|---|---|
| | | |
| <p>LAN cable is not connected. Make sure that the cable is properly connected.</p> | <p>Identifying connection. Wait for the connection to be established. It may take about one minute.</p> | <p>DJ Mixer is connected. It is ready to start the update tool.</p> |

3. Start updating your firmware

- ✓ Close all the applications before you start updating.
- ✓ Depending on the firewall setting of your security software and/or operating system, your computer and mixer may not be connected properly. In such a case, you need to exempt the update tool (DJM2000_vxxx) from your firewall settings.
Please contact customer support of the security software provider and/or operating system for further details regarding firewall settings.

< **STEP1** > Double click "DJM2000_vxxx".
Start update tool.

< **STEP2** > Select a language from the dropdown list and click "OK".




< **STEP3** > Start updating by pressing "START".

- ✓ DO NOT remove power cable and/ or LAN cable during the update.
- ✓ If the Connect dialog box keeps appearing for 30 seconds or longer, the network connection might not be established. Press the "EXIT" button and try connecting the network again to update.



< **STEP4** > Make sure that the update process has been completed.


The following "update completed" message appears when the progress bar on the touch panel reaches 100%.



< **STEP5** > Restart DJ Mixer.

- ✓ If any changes were made in the above "1. Change network settings" of this chapter, please restore the network settings to the previous values.

Check the current version of DJM-2000/2000nexus



< STEP1 >

Press [LIVE SAMPLER(UTILITY, WAKE UP)] button for more than one second to go into "USER SET UP" mode.

< STEP2 >

Select "VERSION No.".

Make sure that the latest version has been installed.
If the update version, "x.xx", is displayed, the update has been successfully completed.

< STEP3 >

Close "USER SET UP" mode.

Press [EXIT] on top-left of the touch panel.



Error Message and Details (for Windows)

| Title | Message | Detail |
|---------------------|--------------------------------------|--|
| Formatting Error | Cannot find the EXE file_I1 | Cannot find the EXE file. Restart the application. |
| | Cannot find the UpdateFile_I4 | Cannot find the update file or the update file is not correct. Download the file and update again. |
| | Cannot connect to the MIXER_I5 | Failed connection with the mixer. Check the network connection and restart the application. |
| | Cannot find the Network Interface_I6 | Cannot find the network setting to connect with the mixer. Check the network connection and restart the application. |
| | Cannot find the Network Interface_I9 | Cannot find network interface to connect with the mixer. Check the network connection and restart the application. |
| Connection Error | Cannot connect the MIXER_C1 | Could not connect with the mixer. Check the network environment and restart the application. |
| | Cannot connect the MIXER_C2 | Could not connect with the mixer. Check the network environment and restart the application. |
| | Cannot send the update data_C4 | Failed data transfer to the mixer. Start the mixer again in update mode and restart the application. |
| Data Transfer Error | Cannot find the UpdateFile_S1 | Cannot find the update file. Download the file and update again. |
| | Cannot find the UpdateFile_S2 | Failed data transfer to the mixer. The file might have a problem. Start the mixer again in update mode and restart the application. |
| | Cannot find the UpdateFile_S3 | Failed data transfer to mixer. Start the mixer again in update mode and restart the application. |

Error Message and Details (for Mac OS)

| Title | Message | Detail |
|---------------------|--------------------------------------|---|
| Formatting Error | Cannot find the EXE file_I2 | Cannot find the EXE file. Check the network connection and restart the application. |
| | Cannot find the EXE file_I3 | Cannot find the EXE file. Check the network connection and restart the application. |
| | Cannot find the UpdateFile_I4 | Cannot find the update file or the update file is not correct. Download the file and update again. |
| | Cannot get the Host name_I7 | Cannot find the host name. Check the network connection and restart the application. |
| | Cannot get the IP Address_I8 | Cannot get IP address. Check the network connection and restart application. |
| | Cannot find the Network Interface_I9 | Cannot find network I/F to connect with the mixer. Check the network environment and restart the application. |
| Connection Error | Cannot connect the MIXER_C1 | Could not connect with the mixer. Check the network environment and restart the application. |
| | Cannot connect the MIXER_C2 | Could not connect with the mixer. Check the network environment and restart the application. |
| | Cannot connect the MIXER_C3 | Could not connect with the mixer. Check the network environment and restart the application. |
| | Cannot send the update data_C4 | Failed data transfer to the mixer. Start the mixer again in update mode and restart the application. |
| Data Transfer Error | Cannot find the UpdateFile_S1 | Cannot find the update file. Download the file and update again. |
| | | Incorrect file path name used for the update file. Only the characters other than one-byte alphabet and numbers may be used. Make sure to use only one-byte alphabet and numbers. Or, copy the update file to another folder with the name as it is and run the file. |
| | Cannot find the UpdateFile_S2 | Failed data transfer to mixer. The file might have a problem. Start the mixer again in update mode and restart the application. |
| | Cannot find the UpdateFile_S3 | Failed data transfer to the mixer. Start the mixer again in update mode and restart the application. |

About trademarks and registered trademarks

- Microsoft, Windows Vista and Windows are either registered trademarks or trademarks of Microsoft Corporation in the United States and/ or other countries.
- Apple, Macintosh and Mac OS are trademarks of Apple Inc., registered in the U.S. and/ or other countries.
- Pioneer is a registered trademark of PIONEER CORPORATION.

© 2012 PIONEER CORPORATION. All rights reserved.

PIONEER CORPORATION

1-1, Shin-ogura, Saiwai-ku, Kawasaki-shi, Kanagawa 212-0031, Japan